



**INSTALLATION INSTRUCTIONS:**

1. HANG IN-LINE ERGO DISCONNECT ON CONDUCTOR WIRE USING THE HANGER.
2. VERIFY WAX IS ON THE KEEPER TO PREVENT GALLING. SEE DETAIL "A" FOR LOCATION.
3. SECURE THE IN-LINE ERGO DISCONNECT USING THE KEEPER. TORQUE TO 40-45 FT-LBS.
4. CUT CONDUCTOR WIRE.
5. BEND BACK AND SECURE CONDUCTOR WIRE OUT OF THE WAY.
6. OPERATE DISCONNECT OPEN AND CLOSED. VERIFY THE BLADE OPENS FULLY IN THE OPEN POSITION AND LATCHES SECURELY IN THE CLOSED POSITION.

**SWITCH SPECIFICATIONS**

CATALOG #: ERG29D-2-V  
 VOLTAGE CLASS: 25.8kV  
 B.I.L. RATING: 150kV  
 CONTINUOUS CURRENT: 900A-RMS (IEEE C37.30.1-2022)  
 MOMENTARY CURRENT: 40,000 AMP, 10 CYCLES  
 25,000 AMP, 3 SECONDS  
 CONDUCTOR RANGE ACSR: 397.5 - 795  
 CLAMPING RANGE: 0.72" TO 1.11"  
 ULTIMATE STRENGTH: 15,000 LBS (BODY)  
 6,000 LBS (PULLING EYE)  
 BODY/KEEPER MATERIAL: A356-T6 ALUMINUM ALLOY  
 SWITCH LIFTING WEIGHT: 36 POUNDS

**SWITCH DESCRIPTION**

SINGLE ERGONOMIC IN-LINE/DISCONNECT SWITCH, 25.8kV, 900A, 150kV B.I.L. RATING, SILICONE INSULATOR, UNDERARM INSTALL

**CONSTRUCTION DRAWING**

DATE: 2/6/26 SCALE: NTS DRAWN BY: IL  
 DRAWING NO. 10315-29-2M-V REVISION NO. 00

00	10435	INITIAL RELEASE	2/6/26	IL
REV. #	ECG#	REVISION DESCRIPTION	DATE	BY
THIS IS A PROPRIETARY AND CONFIDENTIAL DOCUMENT OF MACLEAN POWER SYSTEMS, STOCKTON CA. THIS DOCUMENT CANNOT BE COPIED IN WHOLE OR IN PART WITHOUT THE EXPRESS PERMISSION OF MACLEAN POWER SYSTEMS. THE DOCUMENT IS PROTECTED BY US FEDERAL COPYRIGHT LAW.				

